5618
VHF POWER PENTODE

MINIATURE TYPE

GENERAL DATA

Electrical:

Filament, Coated:

Filament Arrangement	*Series**	*Parallel***	
Voltage	6.0 ± 10%	3.0 ± 10%	ac or dc volts
Current	0.23	0.46	amp

Direct Interelectrode Capacitances:°

Grid No.1 to Plate	0.24	μμf
Input	7.0	μμf
Output	5.0	μμf

° With no external shield.

Mechanical:

Mounting Position	Vertical, or Horizontal with pins No.1 & No.5 in a horizontal plane
Maximum Overall Length	2-5/8"
Maximum Seated Length	2-3/8"
Length from Base Seat to Bulb Top (excluding tip)	2" ± 3/32"
Maximum Diameter	3/4"
Bulb	T-5-1/2
Base	Small-Button Miniature 7-Pin
Basing Designation for BOTTOM VIEW	7CU

Pin 1 – Filament (–)
Pin 2 – Plate
Pin 3 – Grid No.2
Pin 4 – Grid No.3, Int. Shield

Pin 5 – Filament Mid-Tap
Pin 6 – Grid No.1
Pin 7 – Filament (+)

AF POWER AMPLIFIER & MODULATOR—Class A_1

Maximum ICAS Ratings,** *Absolute Values*:

DC PLATE VOLTAGE	300 max.	volts
DC GRID-No.2 (SCREEN) VOLTAGE	125 max.	volts
GRID-No.2 INPUT	2 max.	watts
PLATE DISSIPATION	5 max.	watts

Typical Operation:

Filament Arrangement	*Series**	*Parallel***	
DC Plate Voltage	250	250	volts
DC Grid-No.3 Voltage	0*	0**	volts
DC Grid-No.2 Voltage	75	75	volts
DC Grid-No.1 (Control-Grid) Voltage■	–8	–8	volts
Peak AF Grid-No.1-to-Grid-No.1 Voltage	8	8	volts

*, **, ••, ■: See next page.

5618

5618
VHF POWER PENTODE

Zero-Signal DC Plate Current . .	16	19	ma
Max.-Signal DC Plate Current . .	17.5	20.5	ma
Zero-Signal DC Grid-No.2 Current	1.5	2.0	ma
Max.-Signal DC Grid-No.2 Current	3.5	4.5	ma
Transconductance	3500	3600	μmhos
Effective Load Resistance (plate to plate). . .	12000	12000	ohms
Total Harmonic Distortion. . . .	10	10	%
Max.-Signal Power Output	1.2	1.4	watts

Circuit Values:

Grid-No.1-Circuit Resistance	5000 min.	ohms
	100000 max.	ohms

RF POWER AMPLIFIER & OSCILLATOR—Class C Telegraphy□□
and
RF POWER AMPLIFIER—Class C FM Telephony

Maximum ICAS●● Ratings, ***Absolute Values:***

DC PLATE VOLTAGE	300 max.	volts
DC GRID-No.2 (SCREEN) VOLTAGE.	125 max.	volts
DC GRID-No.1 (CONTROL-GRID) VOLTAGE. . . .	-125 max.	volts
DC PLATE CURRENT	30 max.	ma
DC GRID-No.1 CURRENT	3 max.	ma
PLATE INPUT.	7.5 max.	watts
GRID-No.2 INPUT.	2 max.	watts
PLATE DISSIPATION.	5 max.	watts

Typical Operation:⊕	*Up to 40 Mc*	*At 80 Mc*	
DC Plate Voltage	300	300	volts
DC Grid-No.3 Voltage⊕	0	0	volts
DC Grid-No.2 Voltage□	75	75	volts
	32000	32000	ohms
DC Grid-No.1 Voltage■■ ⊕	-45	-45	volts
	30000	30000	ohms
	1400	1400	ohms
Peak RF Grid-No.1 Voltage. . . .	65	65	volts
DC Plate Current	25	25	ma
DC Grid-No.2 Current	7	7	ma
DC Grid-No.1 Current (Approx.) .	1.5	1.5	ma
Driving Power (Approx.).	0.2	0.3	watt
Power Output (Approx.) ♦ . . .	5.4	5.2	watts

Circuit Values:

Grid-No.1-Circuit Resistance	5000 min.	ohms
	100000 max.	ohms

♦ Useful power output is approximately 5.0 watts for 40 Mc and 4.5 watts for 80 Mc.

*, **, ●●, □, □□, ■, ■■, ⊕: See next page.

5618
VHF POWER PENTODE

FREQUENCY MULTIPLIER

Maximum ICAS[●●] Ratings, ***Absolute Values*****:**

DC PLATE VOLTAGE	300 max.	volts
DC GRID-No.2 (SCREEN) VOLTAGE	125 max.	volts
DC GRID-No.1 (CONTROL-GRID) VOLTAGE	-125 max.	volts
DC PLATE CURRENT	30 max.	ma
DC GRID-No.1 CURRENT	3 max.	ma
PLATE INPUT	7.5 max.	watts
GRID-No.2 INPUT	2 max.	watts
PLATE DISSIPATION	5 max.	watts

Typical Operation:[●]	*Doubler to 80 Mc*	*Tripler to 80 Mc*	
DC Plate Voltage	300	300	volts
DC Grid-No.3 Voltage[⊕]	0	0	volts
DC Grid-No.2 Voltage[□]	75	75	volts
	41000	41000	ohms
DC Grid-No.1 Voltage[🌡]	-125	-125	volts
	68000	68000	ohms
Peak RF Grid-No.1 Voltage	160	160	volts
DC Plate Current	25	25	ma
DC Grid-No.2 Current	5.5	5.5	ma
DC Grid-No.1 Current (Approx.)	1.85	1.85	ma
Driving Power (Approx.)	0.75	0.75	watt
Power Output (Approx.)[◆◆]	4.2	3.4	watts

Circuit Values:

Grid-No.1-Circuit Resistance	5000 min.	ohms
	100000 max.	ohms

◆◆ Useful power output is approximately 3.5 watts for doubler service and 2.7 watts for tripler operation.

" For series filament arrangement, filament voltage is applied between pins No.1 and No.7. The grid-No.1 voltage is referred to pin No.1, and grid-No.3 (pin No.4) is connected to pin No.1.

"" For parallel filament arrangement, filament voltage is applied between pin No.5 and pins No.1 and No.7 connected together. The grid-No.1 voltage is referred to pin No.5 and grid No.3 (pin No.4) is connected to pin No.5.

●● Intermittent Commercial and Amateur Service.

● For dc filament supply.

▬ Obtained from a fixed supply or by a grid-No.1 resistor (30000) or cathode resistor (1400).

□ Obtained from a separate source, or from the plate voltage supply with a voltage divider. Series screen resistor of value shown should be used only where the 5618 is employed as a buffer amplifier and is not keyed.

□□ Key-down conditions per tube without amplitude modulation. Modulation essentially negative may be used if the positive peak of the audio-frequency envelope does not exceed 115% of the carrier conditions.

⊕ Filament may be connected in either parallel or series arrangement. With parallel connection, grid No.3 (pin No.4) is connected to pin No.5; for series operation, connect pin No.4 to pin No.1.

🌡 Obtained from a fixed supply, or by a grid-No.1 resistor of value shown.

RCA

5618

AVERAGE CHARACTERISTICS



5618

RCA

5618

AVERAGE PLATE CHARACTERISTICS

WITH E_{C2} AS VARIABLE



AUG. 12, 1947

TUBE DEPARTMENT

RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

92CM-6882